

## How to make an Irrigatia sand filter

Get a tall yogurt pot and drill a 6mm hole in the lid and 3 or 4 holes around the rim of the pot.



Thread the inlet tube through the hole in the lid, put the filter on the end and ensure it is at the bottom of the pot.

Then cover the filter with washed sand and fit the lid. The water level sensor should be fitted so that one probe is just above the pot, the other hanging alongside. Place the filter in the bottom of your barrel or tank ensuring it stays upright.

Before connecting to your dripper system pump water to waste for 10 minutes, initially the filtered water will be cloudy but is cleared by this action.

